

product specification:

| Item | parameter | |
|-----------------------|---|---|
| Operating System | Linux | |
| Language | English/chinese/customized | |
| Video Compression | H.264 Compression | |
| OSD | overlays information such as date time and vehicle ID | |
| GUI | Graphical user interface setup system parameters with the remote control | |
| Video Record System | video input | 4CH 960P/720P AHD input,aviation connector, 1.0Vp-p, 75Ω |
| | video output | 1 CVBS, 1.0Vp-p, 75Ω,Aviation,Support 1CH Full Screen,4CH Screen view |
| | preview | Support 1 channel and 4 channels preview., Support Manual/Alarm Trigger full screen preview |
| | resolution | 720P/D1/HD1/CIF, MAX:4 channels of 720P and 4 channels of D1 |
| | image quality | 1-4 levels, 1 is the highest level. |
| Video Record System | video standard | PAL: 100f/s , CCIR625 line,50field; NTSC: 120f/s, CCIR525 line,60field; CIF: 256Kbps ~ 1.5Mbps, 8 level video quality optional; HD1: 600Kbps ~ 2.5Mbps, 8 level video quality optional; D1: 800Kbps ~ 3Mbps, 8 level video quality optional; 720P: 4Mbps-6Mbps, multi level video quality optional |
| | record mode | The default setting is auto recording after power on. Timed recording, alarm trigger recording and manual recording are supported. |
| Audio | audio input | 4CH Aviation Plug Input |
| | audio output | 2CH,headphone connect at front panel, BNC Connect on Back panel |
| | compression | G.726 compression, 8KB/s speed |
| Alarm Input | 7CH Alarm Input,1CH AD Input,impulse speed input,Alarm Linkage | |
| Alarm Output | 2CH Alarm Output,Support Light/Sound alarm sensor,Oil/Power cut off | |
| Interface | | 3CH RS232, POS/Fuel Sensor/LED Advertisement Connection |
| | | 1CH 485 Interface,Connect PTZ Camera |
| Wireless Transmission | Support Built in 3G transmission,, WCDMA, CDMA2000,GPRS, EDGE; Built in 4G module optional, TDD-LTE, FDD-LTE | |
| GPS Position | Support Built GPS/BD Module | |
| Storage | HDD | Max 2.5" 1TB HDD |
| | SD Card | Max 128GB SD Card Mirror Recording Keep Data Safety |
| | update | Support USB Updating, SD Card Updating,OTA Remote Updating |
| | file format | H.264 |
| | file system | Special FAT32 File System |
| Record Replay | USB | USB Interface on Front Panel for data back up by U Disk,Hard Disk |
| | video search | Search By Record Time/Record Type etc |
| Record Replay | playback | Max support 4CH Replay /Stop/Fast/Slow at same time Support forward and backward play at the speed of: x 2,x4,x8,x16. |
| | Security | User/Admin 2 Level Different Password |
| Optional Functions | voice call | Support voice call each other |
| | TTS Voice broadcast | Support TTS voice broadcast function. |
| | serial expand | Support LED Advertisement Panel,Oil Sensor, POS,Bus Station Broadcaster,Car OBD,ect.external device |
| Voltage & Power | Power Management | Wide Voltage.Support Timed/Delay off |
| | Input Voltage | DC:+6V - +36V |
| | Output Voltage | +12V~1.5A,+5V~1.5A |
| | Power | Working<5W |
| Working Environment | Temperature | -20°C - +70°C |
| | Humidity | 20% - 80% |

| | | |
|--------|--------|---------------------------|
| Others | Size | 200 (D)* 187(W)* 62(H) mm |
| | Weight | 1.90Kg |

Product Show;



Factory Audit

- SMS Device configure**
- OTA Remote Updating**
- 8CH Full D1 Real time monitor**
- 2TB HDD + 128GB SD Card**

Richmor

OEM/ODM Customized
 Factory Price
 Independent R&D Tech
 Low Moq



RICHMOR TECH

CE

FCC



ROHS





SMS Device configure
OTA Remote Updating
8CH Full D1 Real time monitor
2TB HDD + 128GB SD Card

Richmor

OEM/ODM Customized
Factory Price
Independent R&D Tech
Low Moq





AV Input Cables



AV Output Cable



Power Cable



IO Cables



Remote Control



GPS Antenna



CD (Manual & Software Inside)



SD Mobile DVR



Richmor Brand Package



Standard Package

Client User Graph Interface

移动视频监控平台

欢迎登录, RCMTTEST 系统 实时预览 电子地图 回放管理 信息管理 系统设置

终端列表 轮询列表 我的地图

视频监控 卫星定位 系统调试 用户登录

远程报警 设备管理

监听对讲 驾乘管理 数据报表

用户名: RCMTTEST
密码: *****
服务器: 113.108.120.47
 记住密码 自动登录
登录 退出

1 贵C A6446 - CH1 - 0 KB/S
2 贵C A6446 - CH2 - 24 KB/S
3 贵C A6446 - CH3 - 0 KB/S
4 贵C A6446 - CH4 - 0 KB/S

地址: 马临镇政府
搜索: 地图 卫星

贵C A6446
时间: 2016-03-14 09:50:09 速度: 74.10
公司: 通运集团金融公司 司机: 陈国忠
13511881529
位置: 贵州省遵义市习水县G4215(带道高
状态: 在线, 3G, ACC开启, SD卡(存在), 附
视频 对讲 监听 抓拍 更多

| 终端 | GPS时间 | 位置 | 速度 | 报警 |
|----------|---------------------|------------------------|----------------|----|
| 贵C A6446 | 2016-03-14 09:50:09 | 贵州省遵义市习水县G4215(带道高速公路) | 74.10 km/h(南) | |
| 桂KY7507 | 2016-03-14 09:50:17 | 广西壮族自治区玉林市博白县人民中路38号 | 11.00 km/h(北) | |
| 桂KY7569 | 2016-03-14 09:50:38 | 广西壮族自治区玉林市博白县X403 | 27.00 km/h(西北) | |
| 桂KY7599 | 2016-03-14 09:49:03 | 广西壮族自治区玉林市博白县S216 | 0.00 km/h(东) | |

运行时长: 00:01:04 在线数: 3 / 定损数: 1 / 欠费: 0 / 总数: 11 在线率: 27.27% / 定损率: 9.09%

Application

FUNCTIONS

- Video & Audio real-time monitoring
- Online Vehicle Status
- Satellite Map
- GPS
- Video Storage
- Tracking Display
- Intercom
- Fuel Sensor
- G-Sensor
- Temperature-Sensor

Richmor

OEM & ODM Service

Brasil World Cup Supplier
www.rcmctv.com



Truck
Coach



School Bus
Bus



Police Car
Taxi



Support
All Vehicles

certificate



Richmor

OEM & ODM Service

Brasil World Cup Supplier



Exhibition:

Richmor

CPSE2012 in Shenzhen



CPSE2013

10.29-10.31

4 Booth we have

Welcome you !!!



CPSE2012-- Guangdong TV Report-Shenzhen Richmor



Welcome to contact **Susie** for more details

By Email/wechat, Wechat: Jobs2lovers

By Skype: rcmctvsales4

By Trademanager: cn1001765398

By Mobile phone/Whatsapp: +86-18126263832(Susie Zhou)