

## **Richmor 3G MDVR GPS Takip 3G Gerçek Zamanlı Kayıt MDVR ile, MDR500**

. , Yüksek sıkıştırma oranı, net görüntüler: gelişmiş H.264 Ana Profil video sıkıştırma formatı benimsemeye

küçük bir disk alanı

. Genel dosya biçimini benimsemek. Pazarda ana akım H264 oyuncu Destek

. Video içeriği için güç-off koruma; Elektrik kesintisi olduğunda kayıt bütünselliği sağlamak.

. + 6V ~ + 48V geniş voltaj tasarımı, araçların her türlü için geçerlidir

. Destek 12V / 2A güç çıkışı, diğer akraba cihazlara güç kaynağı olabilir

. Desteği GPS modülü, gerçek zamanlı kayıt araçları hızlandırmak ve otomatik zamanlama olabilir

. Destek 3G video iletim fonksiyonu (EVDO / WCDMA / TD-SCDMA vb isteğe bağlı)

. Profesyonel oynatma analiz yazılımı: GPS track, devlet, hız, kara kutu veri ve ses çalışıyor video görüntüleri senkronize oynatma vs.

. Merkezi yazılımları yönetin; araç görüntü ve alarm bilgilerin gerçek zamanlı iletimini destekleyen

vb

. Küçük ve zarif:

500 serisi: Tüm boyutu 177 (L) x41 (H) x147 (W) mm; Net Ağırlık: 1 KG

### **3G MDVR Resimleri**



## 3G MDVR Şartname

madde	Ekipman parametre	Performans endeksi
sistem	İşlemci	H.264 yüksek performanslı işlemci, güçlü kodlama ve çözme benimseyin
	OS	Gömülü gerçek zamanlı Linux sistemi
	Sistem	PAL / NTSC
	Çalışma arayüzü	Grafik menü çalışma arayüzü(OSD menüsü)
	Güvenlik	Yöneticileri ve kullanıcılar için iki seviyeli şifre koruması
Video	Video girişi	Girdi: 4 CVBS, 1.0V, p-P, 75Ω
	Video çıkışı	Çıktı: 1 CVBS, 1.0V, p-P,75Ω
	İnceleme fonksiyonu	1 kanal veya 4 kanal inceleme modu
	Video Standardı	PAL,25 kare / s ,CCIR625 hattı,50 alan NTSC,30 kare / s,CCIR525 hattı,60 alan
Ses	Ses girişi	Giriş: 1 kanal1,MIC girişi
	Ses çıkışı	Çıktı: 1 kanal,100mV-500mV / 100-500 Ω
	Çıkış seviyesi	1V ~ 2V
	Ses Kaydı	Video ile senkronize
	Ses Sıkıştırma	G.726
Alarm	Alarm girişi	4CH seviye girişi
	Alarm çıkışı	2 CH seviyesi çıkış
Haberleşme Arayüzü	Seri port	Destek 2 adet RS232
Kablosuz haberleşme	Ağ bağlantı noktası	RJ45 10M / 100M Ethernet portu.
	3G	EVDO / WCDMA / TD-SCDMA (isteğe bağlı)
	2.5 / 2.75G	GPRS / CDMA / EDGE (isteğe bağlı)
Küresel Konumlama Sistemi	Desteği dahili / harici GPS modülü; coğrafi koordinatları, hız vb video dosyasına yazılabilir	
Yazılım yükseltme	Destek SD kart yükseltme	

## Aksesuarlar



AV Input Cables



AV Output Cable



Power Cable



IO Cables



Remote Control



GPS Antenna



CD ( Manual & Software Inside)



SD Mobile DVR

## Paket



Richmor Brand Package



Standard Package

**3G MDVR CE FCC ROHS Sertifikasi**





## Kendi tasarlanmış bir yazılım ekran görüntüsü

The screenshot displays a vehicle monitoring software interface. At the top, there are menu options: System, View, and Setting. Below the menu are icons for Map, Video, Track, Record, and Other. The interface is divided into several sections:

- Left Panel:** A tree view under 'Monitor Center(2/7)' showing a hierarchy of devices: 贵CC5656 (with sub-items CH1, CH2, CH3, CH4) and 贵DA6985 (with sub-items 80001, 80003, 80020, 贵80023, 贵C87762).
- Top Center:** Four video feeds labeled 1 through 4, showing interior and exterior views of the vehicle.
- Right Panel:** A map showing the vehicle's location on a road. A tooltip for '贵CC5656' provides details: Time: 2014-11-18 11:14:34, Speed: 73.90 km/h/S, Position: 贵州省遵义市桐梓县兰海高速公路, Status: (Online)ACC, 3G Signal Normal.
- Bottom Center:** A table with columns: Device, Positioning Time, and Position.
 

Device	Positioning Time	Position
贵CC5656	2014-11-18 11:14:34	贵州省遵义市桐梓县兰海高速公路
贵DA6985	2014-11-18 11:14:37	贵州省桐仁市思南县+536
- Bottom:** A status bar showing 'Running: 00:00:35', 'number of alarms storage media: 0', 'Online: 2 / number of set loss: 5 / Arrears: 0 / Total: 7', 'line rate: 28(77)% / Lost rate: 71.43%'.

This screenshot shows the same vehicle monitoring software interface from a different perspective. The map is more prominent, showing the vehicle's location on a road with a tooltip for '贵CC5656' providing details: Time: 2014-11-18 11:15:21, Speed: 72.70 km/h (Southwest), Position: 贵州省遵义市桐梓县兰海高速公路, Status: (Online)ACC ON, SD CardExist, 3G Signal Normal. The video feeds on the right are labeled 1 through 4, showing interior and exterior views. The table at the bottom center is identical to the first screenshot.

## Dünyada Müşteriler



**Desteklerin için teşekkürler!**

**Daha fazla bilgi için Jenny ile irtibat Hoşgeldiniz:**

**E-posta: [jenny@rcmctv.com](mailto:jenny@rcmctv.com)**

**Skype: [rcmctvsales4](https://www.skype.com/people/rcmctvsales4)**